



HiFiBerry AMP2

The HiFiBerry Amp2 is a high-quality, highly efficient Class-D power amplifier for the Raspberry Pi (newer models with 40 pin GPIO connector), that is mounted onto the Raspberry Pi to create a stereo audio system. The speakers just have to be connected directly, which makes it an ideal module for multi-room audio installations.

Facts

- Up to 60W output power
- Capable of driving a pair of 4-8 Ohm speakers
- Fully controllable from the Raspberry Pi
- sample rates up to 192kHz
- Digital-analog conversion included, no need for external DACs or sound cards
- Digital sound transmission for optimal audio performance
- Connects directly to the Raspberry Pi A+/B+/2B/3B/Zero, no additional cables needed
- Only one 12-24V external power supply needed for both AMP2 and the Raspberry Pi, no need for USB power supply anymore
- No soldering required, the AMP2 is directly mounted on the Raspberry Pi A+/B+/2B/3B in less than a minute

| | |
|------------------------------|--------------------|
| Dimensions without package | 5.5 x 6.5 x 2.5 cm |
| Dimensions including package | 9 x 7 x 3 cm |
| Weight | 0.06 kg |
| GTIN | 4260439550514 |

Usage recommendations

- small and elegant music playback devices
- home automation and multi-room audio systems
- solutions that require high-quality sound but unobtrusive appearance

HiFiBerry Deutschland GmbH
Corinthstrasse 53
D-10245 Berlin
Germany

sales@hifiberry.com
www.hifiberry.com



Electrical characteristics

| Parameter | Test conditions | typical |
|----------------------------------|--|---------|
| Output power per channel | Vsupply=12V, Rspk = 40hm, THD+N < 0.1% | 14W |
| | Vsupply=18V, Rspk = 40hm, THD+N < 0.1% | 18W |
| | Vsupply=24V, Rspk = 40hm, THD+N < 0.1% | 20W |
| | Vsupply=12V, Rspk = 80hm, THD+N < 0.1% | 8W |
| | Vsupply=18V, Rspk = 80hm, THD+N < 0.1% | 17W |
| | Vsupply=24V, Rspk = 80hm, THD+N < 0.1% | 28W |
| Maximum output power per channel | Vsupply=12V, Rspk = 40hm, THD+N < 10% | 15W |
| | Vsupply=18V, Rspk = 40hm, THD+N < 10% | 30W |
| | Vsupply=24V, Rspk = 40hm, THD+N < 10% | 44W |
| | Vsupply=12V, Rspk = 80hm, THD+N < 10% | 10W |
| | Vsupply=18V, Rspk = 80hm, THD+N < 10% | 20W |
| | Vsupply=24V, Rspk = 80hm, THD+N < 10% | 38W |